

sanwa®

TOKYO JAPAN

DIGITAL EARTH TESTER

PDR4000



APPLICATIONS AND FEATURES

- Three measurement ranges : 40Ω, 400Ω, 4000Ω
- 3-pole / 2-pole earth resistance measurement
*Optional accessory TL-68 is required for 2-pole measurement.
- Backlight function
- Safety design compliant to IEC61010
- Data hold function
- Relative function
- Auto power-off function
- Capable of measuring interference voltage
- 2mA measuring current

SPECIFICATIONS

	Measuring range	Accuracy
Earth resistance	0~40Ω / 0~400Ω / 0~4000Ω	0.00 ~ 10.00 Ω : ±(2%rdg+10dgt) 10.01 ~ 3000 Ω : ±(2%rdg+3dgt) 3001 ~ 4000 Ω : Out of accuracy guaranteed
Interference voltage	0~400V (40~500Hz)	±(2%rdg+3dgt)
Measuring frequency	820 Hz	
Measuring current at the short circuit	approx. 2mA	
Standard	IEC61010-1 CAT. III 300 V	
Size / Mass	163(L) x 102(W) x 50(D)mm / Approx. 440g (battery included)	
Battery	R6P 1.5V x 6pcs	
Standard accessories included	Test lead set , Auxiliary earth electrodes , Carrying case, Manual , Batteries	



Specifications and external appearance of the product described above may be revised for modification without prior notice.

sanwa®

SANWA ELECTRIC INSTRUMENT CO., LTD.

Dempa Bldg, 4-4 Sotokanda 2-Chome, Chiyoda-Ku, Tokyo 101-0021 Japan
Tel:+81-3-3251-0941 Fax:+81-3-3256-9740

www.sanwa-meter.co.jp

Distributed by